

## DS-PS1-II-WE



The wireless internal sounder DS-PS1-II-WE, supporting 868MHz two-way communication via Cam-X protocol, multiple alarm sounds, strobe light indication, is used for instant alerting when alarm triggered. Meanwhile, it supports two-way audio function for ARCs to do the alarm verification, which can help the users to know what is the real situation on-site immediately.

- 868 MHz two-way wireless communication
- Configurable arming/disarming prompt sound and LED indicator
- Two-way talk via RF transmission
- Buzzer Decibel: 90 to 110 dB
- Long battery life span
- 3 kinds of alarm sounds: fire alarm, panic alarm, and intrusion alarm
- Fully remote configurable through App
- Multiple enrollment methods and easy installation design



## ▪ Specification

Hardware features	
Serial port	1
Tamper-Proof	Supported, front and rear
Buzzer	Supported
Power switch	Power on/off
Mic	Supported
Electrical characteristics	
Operation humidity	10% to 90% (no condensing)
Operation temperature	-10°C to 55°C
Battery type	Four CR123 batteries
Power supply	Support 12 VDC Power Supply
Power interface	12 VDC
Power consumption	Quiescent current: 25 uA Max current: 1.6 A Voltage: 3 V
Battery life span	Up to 2 years (Alarm once a week, 5 mins alarm and 5 mins talk)
Wireless transmission	
RF frequency	868 MHz
RF modulation	2GFSK
RF distance	1000 m (open area)
Wireless technology	CAM-X Wireless Technology
Display	
LED Indicator	Enrollment/Signal (red/green), Alarm(Blue/Red), Two-way audio service(Blue/Red)
General	
Dimension(W × H × D)	130 × 128 × 39.5 mm
Color	White Case (Blue or Red LED Alarm)
Installation method	Wall mounting
Weight	361.0 g

## ▪ Available Model

DS-PS1-II-WE

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com